See discussions, stats, and author profiles for this publication at: https://www.researchgate.net/publication/317480134

A shear-wave seismic system using fullwaveform inversion to look ahead of a tunnelboring machine

Article in Near Surface Geophysics · June 2017

DOI: 10.3997/1873-0604.2017014

TIONS	reads 28
ithors , including:	
 Pawan Bharadwaj Massachusetts Institute of Technology 12 PUBLICATIONS 70 CITATIONS SEE PROFILE 	J. Thorbecke Delft University of Technology 129 PUBLICATIONS 843 CITATIONS SEE PROFILE
Rob Jenneskens Seismic Mechatronics BV 4 PUBLICATIONS 1 CITATION SEE PROFILE	



Extrapolation operator design View project

All content following this page was uploaded by Pawan Bharadwaj on 09 June 2017.

The user has requested enhancement of the downloaded file.

A shear-wave seismic system using full-waveform inversion to look ahead of a tunnel-boring machine

Pawan Bharadwaj^{1*}, Guy Drijkoningen¹, Wim Mulder^{1,2}, Jan Thorbecke¹, Boriszlav Neducza³ and Rob Jenneskens⁴

¹Department of Geoscience and Engineering, Delft University of Technology, The Netherlands

² Shell Global Solutions International BV, Amsterdam, The Netherlands

³ Geo2X, Oulens-sous-Echallens, Switzerland

⁴ Seismic Mechatronics BV, Eindhoven, The Netherlands

Received September 2016, revision accepted March 2017

ABSTRACT

In the near surface with unconsolidated soils, shear-wave properties can often be characterised better and with a higher resolution than compressional-wave properties. To enable imaging ahead of a tunnel-boring machine, we developed a seismic prediction system with a few shear-wave vibrators and horizontal receivers. The boring process is interrupted at regular intervals to carry out active surveys. The vibrators are then pushed against the rock or soil in front of the cutting wheel of the machine. The design of the vibrators is based on linear synchronous motor technology that can generate very low frequencies, starting at 5 Hz. These vibrators generate a force in a direction perpendicular to the tunnel axis. Horizontal receivers measure the particle velocity, mainly due to the horizontally polarised shear waves. Because imaging with conventional migration methods suffers from artefacts, caused by the incomplete aperture and inaccuracies in the assumed velocity model, we use two-dimensional horizontally polarised shear full-waveform inversion to resolve the subsurface shear properties. The classic cycle-skipping problem, which can make the application of fullwaveform inversion cumbersome, is avoided by the capacity of the vibrators to generate low frequencies. In this paper, we demonstrate the capabilities of the proposed seismic system through a number of synthetic and field experiments.

INTRODUCTION

37 While excavating a tunnel with a tunnel-boring machine (TBM), 38 the geology and the ground conditions along the planned-tunnel 39 trajectory need to be investigated in order to safely and effi-40 ciently carry out underground operations. This entails detecting 41 the occurrence of faults, boulders, foundations, pipes, etc., nec-42 essary to avoid hazards that can cause time-consuming delays in 43 the tunnel-boring operations. In order to predict ground condi-44 tions ahead of a TBM, seismic exploration techniques such as 45 data acquisition, processing, and inversion can be deployed. We will discuss how each of those can be applied to tunnel excava-46 47 tion with a TBM.

48 Seismic ground prediction systems for TBM record waves 49 generated by either controlled sources or its rotating cutter 50 wheel. Hauser (2001) and Petronio and Poletto (2002) obtained 51 interpretable seismic data by cross-correlating signals generated 52 by the cutter wheel with pilot signals recorded at reference 53 receivers. Alternatively, seismic interferometry uses cross-corre-

55 *bharadwaj.pawan@gmail.com

54

lation to turn the noise generated by the cutter wheel into useful virtual source records (Poletto and Petronio 2006; Harmankaya et al. 2016). However, artefacts are present in the virtual source records since the location of the sources generating the noise is limited to the cutter wheel. Because of this, ground prediction systems that employ active sources are more successful. In these systems, acquisition is usually carried out with a focus on a particular propagation mode of the seismic waves. The use of Rayleigh waves was proposed by Bohlen et al. (2007) and Jetschny (2010), considering a system that excites and records tunnel surface waves at the tunnel wall behind the cutter head of the TBM. With three-dimensional (3D) elastic modelling, they showed that the high-amplitude Rayleigh waves are converted into high-amplitude shear waves at the front face of the tunnel, and vice versa. P waves are commonly used in hydrocarbon exploration. Kneib, Kassel and Lorenz (2000) describes a seismic system for use in soft soil, which uses P waves from 1.8 to 6 kHz. These are higher compared to the 10- to 120-Hz frequencies commonly used in surface-seismic techniques. The advantage of using shear or S body waves has been demonstrated by

2

3

4

5

6

7

8

9

several authors in the case of soft-soil near-surface applications (Omnes 1978; Helbig and Mesdag 1982; Stümpel et al. 1984; Guy et al. 2003; Haines and Ellefsen 2010). S waves turn out to be very suitable for soft soils since shear waves are not sensitive to the type of fluid or gas in the pores. Hence, estimated shearwave properties using shear waves correlate well with subsurface lithology. In these soils, propagating shear waves often have a 10 shorter wavelength than P waves (Ghose et al. 1998; Miller, Xia 11 and Park 2001; Haines and Ellefsen 2010), resulting in a better 12 resolution while imaging. Also, in the near surface, where the 13 soft-soil TBM usually operates, relative shear-wave variations 14 are much larger than relative P-wave variations.

15 Recorded data are processed to obtain the subsurface param-16 eters that control the seismic wave propagation. A reflectivity 17 image of the subsurface, which depicts the interfaces between different soil types, can be produced by using a subsurface wave-18 19 speed or velocity model. The conventional methods of estimating 20 the velocity model directly from seismic data are not fully auto-21 matic and require time-consuming human interaction, commonly 22 taking several days to obtain the final images. In tunnel-boring 23 operations, this time is not available: results need to be available 24 within an hour or even minutes, to allow for a preventive action 25 when obstacles or potentially dangerous situations ahead of the 26 TBM show up.

27 Most of the current systems for seismic exploration produce 28 reflectivity images using an assumed velocity model instead of 29 an estimated one. Swinnen, Thorbecke and Drijkoningen (2007) 30 discusses an imaging technique based on focusing operators in an assumed model. Tzavaras (2010) applies Kirchhoff pre-stack 31 32 depth migration and Fresnel-volume migration to produce 3D reflectivity images in the case of hard-rock tunnelling. Ashida 33 34 (2001) describes a method to detect the interfaces using data from multi-component receivers. These conventional near-sur-35 36 face imaging techniques all use an assumed velocity model and 37 suffer from various pitfalls (Steeples and Miller 1998). When 38 using shear waves, Miller et al. (2001) has shown that Love 39 waves can stack coherently in a common mid-point gather, lead-40 ing to a wrong interpretation. Incomplete acquisition, due to the 41 limited space available on the TBM, causes recording footprint 42 noise in conventional images. Inaccuracies in the assumed veloc-43 ity model will result in migration images that are not properly 44 focused. Therefore, in tunnelling applications, there is a need for 45 a seismic system that can automatically estimate the wave velocity prior to imaging. Bellino, Garibaldi and Godio (2013) pro-46 47 poses such a fully automatic method, which can estimate the 48 average wave velocity as well as the distance to an interface. 49 Recently, an approach called full-waveform inversion (FWI) 50 (Tarantola 1986; Virieux and Operto 2009) has been used to 51 automatically produce a subsurface velocity model for tunnel 52 exploration (Musayev, Hackl and Baitsch 2013; Bharadwaj et al. 53 2015). FWI is a nonlinear data fitting procedure that minimises 54 the misfit between the recorded and the modelled seismic data, 55 in a least squares sense, to estimate the subsurface parameters. It

requires low frequencies in the data to avoid convergence to local minima caused by the notorious cycle-skipping problem (Virieux and Operto 2009). The advantage of using FWI over conventional imaging techniques is that the least squares imaging condition used in FWI will suppress some of the acquisition-related artefacts (Nemeth, Wu and Schuster 1999).

The application of waveform inversion to near-surface land data is even more challenging than the marine case because of strong elastic effects such as ground-roll and near-surface attenuation. It is difficult to fit the surface waves due to a heterogeneous near surface during inversion. In the tunnel environment, the surface waves propagate along the tunnel wall. In order to properly account for the surface waves, elastic modelling is commonly used for near-surface FWI (Bretaudeau et al. 2013). Even when using elastic modelling, Brossier, Operto and Virieux (2009) illustrated that near-surface FWI generates accurate results via judicious data pre-conditioning and/or muting rather than using surface waves. Moreover, using elastic modelling makes the inverse problem computationally more expensive.

In this paper, we focus on a system that uses horizontally polarised shear (SH) waves (Bharadwaj et al. 2015), because shear waves are better suited for exploration in soft soils than P waves, as discussed earlier. Our objective is to investigate and demonstrate the feasibility of using SH waves in unconsolidated soils for TBM-like situations and geometries. For data acquisition in this system, shear vibrators and receivers are placed on the soil in front of the cutter head to generate and record mainly the SH wavefield. Acquisition is carried out when the TBM is not in operation. The design of the vibrator is based on linear synchronous motor technology (Noorlandt et al. 2015), which can expand the source frequency band to frequencies as low as 5 Hz. For inverting the data, we use FWI to estimate the subsurface shear-wave speed and reflectivity. The capability of the seismic vibrator to generate low frequencies allows us to circumvent the classic problem of cycle skipping. Of course, this assumes that these frequencies can actually be injected into the subsurface, which may not always be the case. The inability to inject low frequencies is illustrated by an acoustic model with a linear vertical velocity gradient in which waves below a certain frequency do not propagate (Kuvshinov and Mulder 2006).

Since the acquired data need to be processed in near real time with current computing technology, we simplified the SH FWI problem to two-dimensional (2D). We applied a crude but simple correction to the measured 3D data to make them resemble 2D data. The 2D approach implicitly assumes invariance in the out-ofplane direction. In that case, the SH waves are decoupled from P, SV, and Rayleigh waves, and we can simplify the elastic wave equation to a 2D SH wave equation. Due to the absence of Rayleigh waves, the observed data are easier to fit compared to P-wave land datasets. However, Love waves that might be present in the observed data are also modelled by solving the 2D SH wave equation (Luo et al. 2010). It should be noted that Love waves are guided waves that are only generated in the presence of a low



S-wave velocity layer close to the sources and receivers. The occurrence of such a layer will be rare as subsurface layering is often nearly horizontal and perpendicular to a cutter-head front.

The remainder of this paper is organised into five sections. The next section describes the data acquisition and pre-processing of our system in more detail. After that, we elaborate on the FWI algorithm used to process the data. In the fourth and fifth sections, we demonstrate the application of the seismic system using synthetic scenarios as well as field data, respectively. The last section summarises the paper.

DATA ACQUISITION AND PRE-PROCESSING

Our system places sources and receivers on the soil along a diameter of the cutter head to generate and record seismic shear waves. Figure 1 shows four possible source–receiver geometries along diameters AA', BB', CC', and DD', respectively. Geometry A is impractical but best illuminates the target. The other geometries use only a few source and receiver positions because of the limited space on a TBM. In the case of a 10-m TBM, geometries B, C, and D also take the following practical considerations into account:

(i) sources and receivers cannot be placed at the same position;

(ii) sources and receivers cannot be placed within a 1-m radius around the centre of the cutter head;

(iii) the minimum distance between two positions, each with either a source or a receiver, is 0.5 m.

The sources and receivers are pushed against the tunnel face to improve the coupling with the soil. The acquisition takes the rotation and advance of the TBM into account. Making use of the rotation of the TBM, different measurements are combined to obtain data along a particular transect, oriented along one of the diameters of the cutter head. As an example, we can combine the measurements at 45° and 225° to obtain data along transect BB' in Figure 1. The new dataset will have eight source positions, and we refer to it as a *combined* dataset. Depending on the rotation speed of the cutter head, combined datasets along three to four transects can be obtained before the TBM advances ahead, closer to a possible target reflector that needs to be imaged.

In the rest of the paper, we consider pre-processing and inversion for a combined dataset along one particular transect. We choose a coordinate system for this transect such that the *x*-axis is always along the transect. The TBM's direction of advance corresponds to the *z*-axis. The vibrator source primarily injects a known sweep as a ground force in the *y*-direction, perpendicular to the transect. As a simplified but useful model, we consider 2D SH waves in the [*x*,*z*]-plane, with the particle velocity in the *y*-direction. Shear vibrators and receivers generate and record only the SH wavefield. This is under the assumption that the medium properties should be invariant in the *y*-direction. Our vibrator source can excite signals down to 5 Hz, a low enough frequency for shallow shear-wave surveying.

We denote the sweep signal in the frequency domain by Φ_s . The uncorrelated recorded data at $\mathbf{x}_r = [x_r, z_r]$ due to a source at $\mathbf{x}_s = [x_s, z_s]$ are given in the frequency domain by

$$Q_{u}(\mathbf{x}_{r}, f; \mathbf{x}_{s}) = \Phi_{s}(f)\Gamma_{s}^{(0)}(\mathbf{x}_{s}, f)\Gamma_{r}^{(0)}(\mathbf{x}_{r})I_{r}(f)G_{3D}(\mathbf{x}_{r}, f; \mathbf{x}_{s}).$$
(1)

In the above equation, $\Gamma_s^{(0)}(\mathbf{x}_s, f)$ is a factor that takes frequencydependent ground coupling at the source position \mathbf{x}_s into account.

2

2

3

4

5

6

7

8

0

10

11

12

13

14

15

16

17

18

19

20

21

22

23

24

25

26

27

41

42

Similarly, $\Gamma_r^{(0)}(\mathbf{x}_r)$ denotes coupling at the receiver position \mathbf{x}_r , and $I_r(f)$ describes the frequency-dependent instrument response of the receivers used in the survey, which is assumed to be known. G_{3D} is the 3D Green's function or impulse response of the Earth. After acquiring the data, a cross-correlation with the source-sweep signal ϕ_s in the time domain or multiplication with the complex-conjugate spectrum Φ_s^* in the frequency domain is performed. Furthermore, to broaden the bandwidth of the data, a spectral division with the amplitude spectrum of the sweep and the amplitude spectrum of the instrument response is carried out. This results in correlated data $Q^{(3D)}$, given in the frequency domain by

$$\mathcal{Q}^{(3D)}(\mathbf{x}_{s},\mathbf{x}_{r},f) = \frac{\Phi_{s}^{*}(f)\Phi_{s}(f)\Gamma_{s}^{(0)}(\mathbf{x}_{s},f)\Gamma_{r}^{(0)}(\mathbf{x}_{r})I_{r}(f)G_{3D}(\mathbf{x}_{s},\mathbf{x}_{r},f)}{(|\Phi_{s}(f)|^{2}+\varepsilon_{1})(|I_{r}(f)|+\varepsilon_{2})}, \quad (2)$$

where ε_1 and ε_2 are small stabilisation factors.

We invert the combined data along each transect individually as if line sources, which are oriented along the direction perpendicular to the transect, were used. This is a consequence of the 2D assumption. Since, in reality, we use nearly point-like 3D sources, we apply an approximate correction to the combined data, $q^{(3D)}$, in the time domain to make them resemble 2D data. We let

$$q^{(2D)}(\mathbf{x}_s, \mathbf{x}_r, t) = \sqrt{t} q^{(3D)}(\mathbf{x}_s, \mathbf{x}_r, t),$$
(3)

28 where the correlated data before and after applying correction are denoted by $q^{(3D)}$ and $q^{(2D)}$, respectively. This correction 29 mainly compensates for the difference in geometrical spreading 30 of the waves (Wapenaar, Verschuur and Herrmann 1992); we 31 skipped the customary phase correction by \sqrt{if} , which is handled 32 instead by including a source-related filter as unknown during 33 34 the inversion. The correction replaces the 3D Green's function 35 Q_{3D} in equation (2) with the 2D Green's function Q_{2D} . After this 36 correction, additional pre-processing methods, such as band-pass 37 filtering, shot-gather normalisation, and time-domain tapering, are performed on $q^{(2D)}$ to obtain the pre-processed observed data 38 39 $q_{\rm p}$, used for inversion. 40

Finally, the inversion results from datasets along different transects can be combined into a single 3D image.

43 TWO-DIMENSIONAL HORIZONTALLY POLARISED 44 SHEAR FULL-WAVEFORM INVERSION

45 An important characteristic of our ground prediction seismic 46 system is its ability to automatically produce subsurface maps of 47 the shear-wave velocity, c_{e} , and/or mass density, ρ . This is 48 mainly achieved by the combination of a specially designed 49 seismic vibrator, based on linear synchronous motors and capa-50 ble of generating low frequencies, and FWI. Once these maps are 51 produced, the reflectivity image of the subsurface can be 52 obtained by taking the derivative of the estimated S-wave imped-53 ance in either the x- or z-direction or by taking the Laplacian. 54 Applying the derivative boosts the reflectors, the interfaces 55 between different materials where seismic waves are reflected.

To compute the modelled data, we solve the 2D SH wave equation in terms of the particle velocity in the out-of-plane or *y*-direction. We use a time-domain staggered-grid finite-difference solver (Virieux 1984) for the forward modelling. To properly account for the effect of the tunnel wall on the wave propagation, we impose the appropriate Neumann boundary conditions.

Next, we will discuss the objective function to be minimised during FWI.

Least squares functional with source filters and receivercoupling factors

The classic least squares inversion (Tarantola 1984; Pratt, Shin and Hicks 1998; Virieux and Operto 2009; Fichtner 2010; Maurer *et al.* 2012) minimises the difference between the pre-processed observed data and the modelled data iteratively. The objective function with unknown source-related filters and receiver-coupling factors along with the modelled data is given by

$$J_{ls} = \frac{1}{2} \sum_{s} \sum_{r} \sum_{t} \sum_{r} \left[p(\mathbf{x}_{r}, t; \mathbf{x}_{s}) *_{t} \gamma_{s}(\mathbf{x}_{s}, t) \gamma_{r}(\mathbf{x}_{r}) - q_{p}(\mathbf{x}_{r}, t; \mathbf{x}_{s}) \right]^{2}.$$
 (4)

Here, $*_t$ denotes convolution in time. We denote the source filters in the time domain and receiver-coupling factors by $\gamma_s(\mathbf{x}_s, t)$ and $\gamma_r(\mathbf{x}_r)$, respectively. Note that the receiver-coupling factors are chosen to be time-independent scalars. The pre-processed observed data and the modelled data are denoted by q_p and p, respectively. For further analysis, we consider the data in the frequency domain where convolution in time corresponds to a simple product operation. Using Parseval's theorem, we rewrite the objective function in equation (4) by Fourier transforming the data from time t to frequency f as

$$J_{ls} = \frac{1}{4\pi} \sum_{s} \sum_{r} \sum_{f \ge 0} \left| P(\mathbf{x}_{r}, f; \mathbf{x}_{s}) \Gamma_{s}(\mathbf{x}_{s}, f) \Gamma_{r}(\mathbf{x}_{r}) - Q_{p}(\mathbf{x}_{r}, f; \mathbf{x}_{s}) \right|^{2},$$
(5)

where we used the fact that p, q_p , γ_s , and γ_r are real valued. Here, P, Q_p , Γ_s , and Γ_r denote the frequency-domain representations of p, q_p , γ_s , and γ_r , respectively. Note that $\Gamma_r = \gamma_r$, as the receiver-coupling factors are frequency independent.

During the inversion, Γ_s and Γ_r are to be estimated in addition to the medium parameters. The source filters and the receivercoupling factors compensate for additional unknowns such as source signature and ground coupling at source and receiver locations in the seismic experiment. In order to understand their significance, we consider a case in which the modelled data are generated for the correct medium parameters with a source wavelet Φ . For that case, we express the pre-processed observed data discussed in the previous section as

$$\mathcal{Q}_{p}(\mathbf{x}_{s},\mathbf{x}_{r},f) \approx \frac{\Phi_{s}^{*}(f)\Phi_{s}(f)\Gamma_{s}^{(0)}(\mathbf{x}_{s},f)\Gamma_{r}^{(0)}(\mathbf{x}_{r})I_{r}(f)G_{2D}(\mathbf{x}_{s},\mathbf{x}_{r},f)}{(|\Phi_{s}|^{2}+\varepsilon_{1})(|I_{r}|+\varepsilon_{2})}$$
(6)

$$\approx \underbrace{\frac{\Phi_s^*(f)\Phi_s(f)\Gamma_s^{(0)}(\mathbf{x}_s,f)I_r(f)}{\Phi(f)(|\Phi_s|^2 + \varepsilon_1)(|I_r| + \varepsilon_2)}}_{\Gamma_s(\mathbf{x}_s,f)} \underbrace{\frac{\Gamma_r^{(0)}(\mathbf{x}_r)}{\Gamma_r(\mathbf{x}_r)}} P(\mathbf{x}_s,\mathbf{x}_r,f).$$
(7)

It is obvious from the above equation that factors Γ_s and Γ_r are required to match the modelled data to the observed data even when the correct medium parameters are used.

We use a gradient-based technique to minimise the functional J_{ls} . Hence, we first derive the expressions for the gradient of J_{ls} with respect to the modelled data, source filters, and receivercoupling factors. These are denoted by $\nabla_p J_{ls}$, $\nabla_{\gamma_s} J_{ls}$ and $\nabla_{\gamma_r} J_{ls}$, respectively. Then, we will explain our optimisation strategy.

Gradient with respect to medium parameters

2

3

4 5

6

7

8

9

11 12

22

23

24

25

26

27

28

29

30

31

32

33

34

35

36

37

38

39

40

41

42

43

44

45

46

47 48

49

50

51

13 The gradient of J_{l_e} with respect to the medium parameters, c_e and 14 ρ , is required to update the subsurface maps. It is computed by 15 correlating the forward-propagated source wavefield with the 16 adjoint wavefield at each point in the subsurface. The adjoint 17 wavefield is generated by injecting the adjoint source functions 18 $\nabla_{\mathbf{n}} J_{\mathbf{k}}$ from the receiver positions. In order to compute the adjoint 19 source functions for the least squares functional with source fil-20 ters and receiver-coupling factors, the following steps are per-21 formed sequentially:

- (i) source filters and receiver-coupling factors are applied to the modelled data;
- (ii) the difference between the data after applying filters and the observed data is calculated;
- (iii) the difference is cross-correlated with the source filters and multiplied with receiver-coupling factors.

In order to derive an expression for $\nabla_p J_{ls}$, we rewrite equation (5) using the real and imaginary parts of the absolute-valued data as

$$J_{b} = \frac{1}{4\pi} \sum_{s} \sum_{r} \sum_{f \ge 0} \{ [\operatorname{Re}(P) \operatorname{Re}(\Gamma_{s})\Gamma_{r} - \operatorname{Im}(P) \operatorname{Im}(\Gamma_{s})\Gamma_{r} - \operatorname{Re}(Q_{p})]^{2} + [\operatorname{Im}(P) \operatorname{Re}(\Gamma_{s})\Gamma_{r} + \operatorname{Im}(\Gamma_{s}) \operatorname{Re}(P)\Gamma_{r} - \operatorname{Im}(Q_{p})]^{2} \}.$$
 (8)

We now differentiate the above equation with respect to the real and imaginary parts of the modelled data *P* to obtain

$$\nabla_{p} J_{ls} = \nabla_{\mathrm{Re}(P)} J_{ls+i} \nabla_{\mathrm{Im}(P)} J_{ls}$$
$$= \frac{1}{2\pi} \Big[P(\mathbf{x}_{r}, f; \mathbf{x}_{s}) \Gamma_{s}(\mathbf{x}_{s}, f) \Gamma_{r}(\mathbf{x}_{r}) - Q_{P}(\mathbf{x}_{r}, f; \mathbf{x}_{s}) \Big] \Gamma_{s}^{*}(\mathbf{x}_{s}, f) \Gamma_{r}(\mathbf{x}_{r}) , \quad (9)$$

where the superscript * denotes complex conjugation. Alternatively, the Wirtinger calculus can be used to derive an expression for $\nabla_p J_{ls}$.

Using the chain rule, we can write the derivative of the functional with respect to the modelled data in the time domain as

$$\nabla_{p} J_{ls} = \left[p(\mathbf{x}_{r}, t; \mathbf{x}_{s}) *_{t} \gamma_{s}(\mathbf{x}_{s}, t) \gamma_{r}(\mathbf{x}_{r}) - q_{p}(\mathbf{x}_{r}, t; \mathbf{x}_{s}) \right] \otimes_{t} \gamma_{s}(\mathbf{x}_{s}, t) \gamma_{r}(\mathbf{x}_{r}), \quad (10)$$

where \otimes_{t} denote cross-correlation.

Updating source and receiver filters

In order to compute the gradient of the objective function in
equation (8) with respect to the source filters, the same steps as
those for the gradient in the preceding subsection are followed
except for step (iii), where the difference is cross-correlated with

the modelled data and multiplied with the receiver-coupling factors. Now, an additional summation over the receiver coordinate is also performed. This leads to

$$\nabla_{\gamma_s} J_{ls} = \sum \left[p(\mathbf{x}_r, t; \mathbf{x}_s) *_t \gamma_s(\mathbf{x}_s, t) \gamma_r(\mathbf{x}_r) - q_p(\mathbf{x}_r, t; \mathbf{x}_s) \right] \otimes_t p(\mathbf{x}_r, t; \mathbf{x}_s) \gamma_r(\mathbf{x}_r).$$
(11)

Similarly, the gradient with respect to the receiver-coupling factors can be computed as

$$\nabla_{\gamma_r} J_{ls} = \sum_{s} \sum_{r} \left[p(\mathbf{x}_r, t; \mathbf{x}_s) *_t \gamma_s(\mathbf{x}_s, t) \gamma_r(\mathbf{x}_r) - q_p(\mathbf{x}_r, t; \mathbf{x}_s) \right] \otimes_t p(\mathbf{x}_r, t; \mathbf{x}_s) \otimes_t \gamma_s(\mathbf{x}_s, t).$$
(12)

Optimisation strategy

We estimate the unknown medium parameters, source filters, and receiver-coupling factors that affect equation (4) by using an optimisation strategy outlined by the flowchart in Figure 2. We use the conjugate-gradient minimisation scheme that uses the gradients of the objective function with respect to the unknowns. The inputs of the optimisation strategy are the pre-processed observed data, the initial values of the source filters, the receivercoupling factors, and the medium parameters. Initially, we choose the receiver-coupling factors to be equal for all the receivers, for instance, $\gamma_r = 1$, and the source filters to be all zero. The initial shear-wave velocity model is a homogeneous one, and the velocity is chosen based on the move-out of the direct arrivals in the observed data.

The outermost loop in our strategy runs over the frequency band (i_b) of the observed data selected for inversion. This approach corresponds to multi-scale FWI (Bunks *et al.* 1995; Boonyasiriwat *et al.* 2009), where we first invert the low-frequency data and then gradually include higher frequencies. The innermost loop consists of two round-trips (i_r) for the observed data in a given frequency band. The output of the first round-trip is used as input to the second. In each round-trip, the unknowns that should minimise J_{i_b} are estimated in the following order:

- source-related filters, γ_s, having both positive and negative lags, where a maximum lag time is chosen to prevent error leakage from medium parameters;
- (ii) receiver-coupling factors, $\gamma_{,}$, which should be positive;
- (iii) the velocity, c_s, everywhere ahead of the TBM, by fitting both the direct arrivals and the reflections in the observed data;
- (iv) the velocity, c_s , in a region with roughly one dominant wavelength away from the TBM, so that the minimisation mainly fits the arrivals reflected off the scatterers in the region. This is accomplished by muting the gradient close to the TBM.

While updating one of the unknowns, the other unknowns are kept constant. During step (iv), we focus on fitting only the reflections in the data because the direct arrivals are often stronger and dominate the inversion during step (iii). Note that the limited maximum offset causes refractions and diving waves to be absent. The motivation behind performing more than one round-trip is that the estimate of the source and receiver filters is improved during the second round-trip when an updated velocity model from the first

Synthetic Scenario(s)		Background Material	Anomaly
Abrupt Change and Fault Region		Sand	Clay
	$c_{s} (m s^{-1})$	500	160
	ho (g cm ⁻³)	2.2	1.8
Inclusion		Clay	Limestone
	$c_{s} (m s^{-1})$	160	1300
	ρ (g cm ⁻³)	1.8	2.4

Table 1 Shear properties of some materials as used in synthetic scenarios, given as shear-wave velocity c_s and mass density ρ .

Table 2 Forward modelling parameters used for different examples.

Example	Source wavelet for <i>q</i> Fourth-order minimum		Record time (s)
		Butterworth source wavelet for p	
Abrupt Change (synthetic)	40-80-300-400 Hz Ormsby	40–400 Hz	0.1
Inclusion (synthetic)	40 Hz Ricker	1–150 Hz	0.15
Fault Region (synthetic)	40-80-300-400 Hz Ormsby	40–400 Hz	0.1
Inclusion (field)	unknown	10–120 Hz	0.35
	ulikilowii	10-120 112	0



Figure 2 Flowchart depicting the optimisation strategy used to estimate source, receiver filters and shear-wave velocity in the medium. The subscript *b* in i_b stands for the frequency band, and the subscript *r* in i_r stands for round-trip. N_b denotes the total number of frequency bands inverted.

round-trip is available, assuming that each step reduces the error between modelled and observed data. Similarly, the velocity model is better estimated in the second round-trip since improved filters are applied to the modelled data.

SYNTHETIC SCENARIOS

In order to evaluate the performance of 2D SH FWI in a TBM-like setting, we present results from three typical hazardous scenarios from the tunneling industry. Table 1 lists the values for the seismic shear-wave properties of various subsurface materials, used to generate 2D synthetic c and ρ models. Random velocity and density perturbations (approximately 10% of the background) are added to the synthetic models to make them more realistic. For each scenario, synthetic models serve as input to the 2D SH finitedifference wave-equation solver to generate synthetic "observed" data. Table 2 lists the parameters chosen for the forward modelling. The records corresponding to each receiver are then multiplied with a random number between 0.2 and 1 to introduce receiver-coupling factors $\Gamma_r^{(0)}(\mathbf{x}_r)$, as in equation (1). As specified in Table 2, we deliberately chose different source wavelets for the observed data and for the initially modelled data so that the estimation of the source filter is necessary during the inversion.

We invert only for the shear-wave speed, c_s , while the source filter is assumed to be independent of the source location. Table 3 summarises the inversion parameters. The mass density, ρ , is taken as a constant during the inversion. The tunnel axis is assumed to be at a depth of 10 m below the surface a z = 0. The sources and receivers are constrained to depths between 5 and 15 m below the surface, thereby assuming a TBM diameter of 10 m (see, e.g., Figure 1). Absorbing boundary conditions are applied at the surface. For a quantitative evaluation of the output model vectors, e.g., **m**, we used a correlation measure with respect to a reference model vector, **m**₀, given by

$$C_{\mathbf{m},\mathbf{m}_0} = \frac{\langle \mathbf{m}, \mathbf{m}_0 \rangle}{\langle \mathbf{m}_0, \mathbf{m}_0 \rangle},\tag{13}$$

where < .,. > denotes zero-lag correlation.

3

8 9

11 12

13 14 15

17 18

20

23

25

26

27

28

29

30

31

33

34

36

37

38 39

40

41

42

43

44

45

46

47

48

49

50

51

52

53 54

55

© 2017 European Association of Geoscientists & Engineers, Near Surface Geophysics, 2017, 15, 210-224

Scenario A: Abrupt Change

This scenario defines a sudden change in geology, for instance, when a compacted sand layer lies next to clay. Figure 3(e,j) shows 2D cross sections of the shear-wave velocity and mass density models for such a scenario. Here, the sources and receivers are positioned in the sand, and we consider all the four acquisition geometries shown in Figure 1. As listed in Table 2, we used a 40–80–300–400 Hz Ormsby source wavelet, plotted in Figure 4, to generate the observed seismic data. To generate the modelled data, we used a 40–400 Hz fourth-order minimum-phase

 Table 3 Inversion parameters used in examples.

Scenario	Band 1 (Hz)	Band 2 (Hz)	Band 3 (Hz	a) Band 4 (Hz)	Length of $\gamma_s(s)$	Initial c_s (m s ⁻¹)
Abrupt Change (synthetic)	40-70	40-100	40-200	40-400	0.01	400
Inclusion (synthetic)	full				0.01	170
Fault Region (synthetic)	40–70	40–100	40-200	40-400	0.01	400
Inclusion (field)	full				0.04	110
		(f)		(k)	Figure 3 S Change. Th using geome are plotted in	Scenario A: Abrup le output c_s model etries A, B, C, and I n (a), (b), (c), and (d)
$\frac{1}{2} \frac{10}{16} $ (b)		(g)			respectively. horizontal an of the c_s m (f)–(i) and	The corresponding nd vertical derivative todels are plotted in (k)–(n), respectively
$ \begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \end{array}\\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \begin{array}{c} \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} \\ \end{array} $ } \begin{array}{c} \end{array} \\		0.63		0.74	The c_s (e) a to generate to shown as we pattern indic the TBM. T ures of the o tries B, C, a	nd ρ (j) models use the observed data ar ell. The cross-hatche cates the location of the correlation meas putputs using geome and D are also giver
(c) (f)		(h) 0.34		(m) 0.18	where the outputs using geo A are chosen for reference.	
(a) (a) (a) (a) (a) (b)	ł	(i) 0.24		(n) 0.01		
(e) $ \begin{array}{c} $	0	(j) ($7.5 15 c$	$ \begin{array}{c} \text{(a)} -(\text{d}) \\ & 300 \\ & 400 \\ & 500 \\ & 600 \\ & 700 \\ & (\text{m s}^{-1}) c (\text{i}) \end{array} $	(e) (j) 200 1. 400 2. 600 2. 2. m s ⁻¹) ρ (g cm ⁻²	6 8 2 4 3)	

© 2017 European Association of Geoscientists & Engineers, Near Surface Geophysics, 2017, 15, 210-224



Figure 4 For the abrupt-change scenario, the source wavelet used to generate the synthetic *observed* data is plotted in black. The estimated source filter γ_s applied to the modelled-data wavelet ϕ is plotted in red, when using acquisition geometry B.

models with respect to x and z, respectively. The abrupt change in geology is well imaged with acquisition geometries A and B, although better with A than with B. This is caused by the fact that more sources and receivers are used in acquisition geometry A. In both cases, the horizontal reflectivity models depict a reflector that is positioned correctly. In addition to the first reflector, the inversion has also imaged a ghost reflector that can be misinterpreted as a second reflector. Acquisition geometries C and D were unsuccessful in illuminating the target reflector, particularly in the centre, because they use a smaller number of sources. As shown in Figure 3, the correlation measure (equation (13)) decreases (by a factor of 2) for these geometries compared to geometry B, where the outputs using geometry A are chosen as reference. This indicates that one should aim for an acquisition with properly distributed sources and receivers. In all cases, the estimated source filters and receiver-coupling factors after inversion are close to their true values. In the case of geometry B, the source wavelet used to generate the observed data and the estimated source filter γ_{a} applied to the modelled-data wavelet ϕ are plotted in Figure 4. Figure 5 shows the estimated and true receiver-coupling factors.

5

Advance of the TBM

As the TBM advances, it approaches the subsurface target that we would like to image. Our system performs inversion at each stage of advance separately. Often, the target is better illuminated when the TBM comes closer, resulting in a better image. To demonstrate this fact, we consider the current scenario with three stages of advance and with acquisition geometry B. During the first stage, the TBM is far away from the target reflector as in Figure 6(a). The position of the target reflector cannot be determined accurately because of the lack of offset-dependent information, which determines the background velocity. The image of the target reflector in the output reflectivity model in Figure 6(d) appears closer to the TBM than in the actual synthetic model in Figure 6(g). It can be noticed that, in the output velocity model (Figure 6(a)), the velocity between the reflector and the TBM is lower than the actual value. The inversion results from the second stage, Figure 6(b,e), show that the target is better illuminated

Figure 5 For the abrupt-change scenario, the true and estimated receivercoupling factors are plotted in black and red, respectively. Acquisition geometry B is used.

Butterworth wavelet. The maximum recording time for the observed and modelled data is 0.1 s. The source filter, γ_s , has both positive and negative lags with a maximum lag time of 0.01 s. We applied multi-scale FWI by first inverting the data between 40 and 70 Hz, followed by three bands, namely, 40–100 Hz, 40–200 Hz, and 40–400 Hz, as shown in Table 3. We start the inversion from a homogeneous velocity model with $c_s = 400$ m/s. As already mentioned, the mass density is kept constant during the inversion.

1 The updated velocity models after inversion with acquisition 2 geometries A, B, C, and D are displayed in Figure 3(a–d). The 3 cross-hatched pattern indicates the location of the TBM. The 4 horizontal and vertical reflectivity models, shown in Figure 3(f– 5 i) and (k–n), are obtained by differentiating the output velocity

7

8

9

1

In practice, it is possible to use the inversion outputs from a particular stage as initial models for the next stage. Also, the datasets from two or three consecutive stages can be combined to perform joint inversion.

Scenario B: Hard-rock Inclusion

In this scenario, we used the c_{c} and ρ models shown in Figure 11 12 7(e,j). The models represent a rock-type inclusion in a soft-soil 13 environment. Often, this type of inclusion is more or less hori-14 zontal in young sediments. We use clay as the background 15 medium and limestone for the hard inclusion. The shear-wave 16 velocity of the propagating waves in clay is lower than in sand or 17 limestone, and high frequencies are attenuated due to losses. 18 Based on our experience with field experiments, we used a 19 40-Hz Ricker wavelet to generate the observed seismic data. The 20 modelling and inversion parameters for this scenario are summarised in Tables 2 and 3, respectively. In this example, we invert the observed data only in a single frequency band because 23 the initial homogeneous velocity model has roughly the same background velocity as the actual model. The output velocity 25 models, horizontal-reflectivity models, and vertical-reflectivity 26 models after inversion using different acquisition geometries are 27 plotted in Figure 7. The correlation measure is only slightly 28 lower for geometries C and D compared to geometry B, where 29 the outputs using geometry A are chosen as reference. In all 30 cases, we were able to image only the tip of the inclusion in front

of the TBM. This was to be expected since the source cannot illuminate the sides of the inclusion, in a way that would cause waves to be reflected back to the receivers. All the acquisition geometries image the tip of the inclusion well. However, it can be seen that using less source positions, as in the case of geometries C and D, causes more artefacts in the output velocity models.

Scenario C: Fault Region

Figure 8(e,j) shows the velocity and density models corresponding to this scenario. The aim is to predict the characteristics of the fault region, particularly its width and filling material. We consider the case where the geology is the same on both sides of the fault region. The medium inside the fault region is considered to be clay, and the background medium is considered to be sand. Since the sources and receivers are in the sand area, we used the same modelling and inversion parameters (Tables 2 and 3) as those for the abrupt-change scenario. The output velocity models, horizontalreflectivity models, and vertical-reflectivity models after inversion with the different acquisition geometries are displayed in Figure 8. The fault region model is only imaged properly in the case of geometries A and B. Again, when compared to geometry B, the correlation measure is lower by almost a factor of 2 when using geometries C and D, because of the smaller number of sources and receivers. The width of the reconstructed fault structure exceeds the actual width. The exact velocity of the filling material, clay, cannot be determined by the inversion because of the limited aperture. However, the horizontal-reflectivity images depict the bound-



Figure 6 Inversion results during three stages of advance of the TBM for Scenario A using acquisition geometry B. The output velocity models from inversion are plotted in (a)–(c). The horizontal derivatives of the output velocity models are plotted in (d)–(f), which depict the target reflector. The cross-hatched pattern indicates the location of the TBM. The c_s (g) and ρ (h) models used to generate the observed data are also plotted.

^{© 2017} European Association of Geoscientists & Engineers, Near Surface Geophysics, 2017, 15, 210-224

aries of the fault region. Note that the imaged reflector corresponding to the outer boundary of the fault region might also be misinterpreted as a ghost reflector in Figure 3.

FIELD TEST: INCLUSION

So far, we have considered synthetic scenarios. We will continue with a scenario that was built in the field. This took place at a site near Eindhoven Airport in the Netherlands, where a number of scenarios were built. Here, we will discuss only one of them, namely, an inclusion. A TBM setting was simulated by having a fixed spread at the surface as if that spread would represent the source(s) and receivers on the cutter head of a TBM. Therefore, this mimicks a TBM measuring in the vertical rather than the horizontal direction, as considered in the preceding section. The rotation of the cutter head was simulated by rotating the spread at an angle of 60° compared to the previous one, keeping the central point of the spread fixed.

In order to simulate an inclusion, a vertical concrete tube 1.2 m in height and 0.6 m in diameter was filled with gravel and placed at a depth of 6 m, exactly below the middle point of the spread. The tube was buried underneath a thick cover of clay. The clay cover was subsequently peeled off, mimicking the advancement of the TBM. Here, we will show the results after removing 2 m of the clay cover, when the concrete tube was 4 m, below the acquisition surface; in Figures 10 and 11, the tube is situated at z = 6 m, while the acquisition surface was at z = 2 m.



^{© 2017} European Association of Geoscientists & Engineers, Near Surface Geophysics, 2017, 15, 210-224

Figure 8 Same as Figure 3, except

for Scenario C: Fault Region.



Field Experiment in the Netherlands



Figure 9 Field acquisition with the shear-wave vibrator (red box), especially designed for this application, and the receivers (blue box) along a transect (dashed line) similar to what is typical for a TBM situation.

As for the receivers, the experiment was conducted with 17 10-Hz horizontal SM9[©] geophones from the company ION, evenly spaced at 0.5 m from x = -4 m to 4 m, mimicking the case of a TBM with a diameter of 8 m. For the type of seismograph, we used a 24-bit Sigma Delta system Geode[®] from the company Geometrics. The geophones measure the out-of-plane component of the particle velocity, in this case, the SH waves. As for the source, we generated an out-of-plane component of the force, i.e., generating SH waves. The shear-wave vibrator was placed at the positions of the 1st, 3rd, 5th, 13th, 15th, and 17th receivers; hence, at x = -4 m, -3 m, -2 m, 2 m, 3 m, and 4 m. With the source placed there, the geophone was removed from that particular position and put back when the source was moved to the next position. Figure 9, taken during the acquisition, shows a picture of the whole set-up.



Figure 10 The pre-processed data and inversion results of the first transect. (a) Observed shot gather for a source at x = 4 m. (b) Modelled shot gather after inversion. (c) Estimated shear-wave velocity model of subsurface. (d) Image of subsurface depicting the inclusion. The actual location of the inclusion is marked by the red box.

We used the newly developed shear-wave vibrator that allowed us to input a broadband signal into the ground, namely, a linear sweep from 5 to 120 Hz, including the low frequencies required by FWI to perform the processing in a fully automated way.

Observed shot gathers for a source at x = 4 m after preprocessing are plotted in Figures 10(a) and 11(a). The preprocessing consisted in applying the correlation with the input sweep, the correction for the amplitude of the receiver's transfer function, and the correction for 3D-to-2D amplitudes, all according to equation (3). We fitted the recorded shot gathers starting from a homogeneous Earth model with $c_s = 110$ m/s and $\rho = 1$ g/cm³. The mass density model is not updated during the inversion, and only the data in the bandwidth 50–120 Hz are used. Unfortunately, frequencies below 50 Hz had to be muted to suppress the noise from nearby vehicles. We noticed that such a muting operation did not cause severe cycle-skipping problems in this test.

We use the optimisation strategy shown in Figure 2. After inversion, the modelled data, plotted in Figures 10(b) and 11(b), match the observed data quite well. Figures 10(c) and 11(c) show the final output velocity model for both transects. Figures 10(d) and 11(d) depict the vertical derivatives of the output velocity models. Note that in Figure 11(d), there is a slight mismatch with

55

the true position of the buried target. In Figure 11(b), there is a data mismatch around an offset of 4–5 m. For each transect, the inversion of pre-processed data takes about half an hour on six compute cores. The results were used for interpretation, and we were able to detect a high-velocity anomaly, corresponding to the location of the concrete-tube inclusion. This demonstrates the success of our SH-wave seismic system in producing subsurface images, including the possibility of having a fully automatic system.

DISCUSSION AND CONCLUSIONS

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

During the field experiment, the recorded signals below 50 Hz are masked by noise due to nearby vehicles. In these situations

with unreliable low frequencies in the data, the inversion is prone to suffer from the cycle-skipping problem (Mulder and Plessix 2008). The cycle-skipping problem is severe only when recovering low-wavenumber anomalies, which is not the case in our field example. Alternative inversion algorithms are proposed by many authors (van Leeuwen and Mulder 2010; Bozdağ, Trampert and Tromp 2011; Bharadwaj, Mulder and Drijkoningen 2016; Li and Demanet 2016) to reduce the severity of this problem.

In the examples of this paper, we only estimated the subsurface shear-wave velocity. In addition to that, FWI can also estimate the mass density of the subsurface provided that the inverse problem is properly regularised with necessary constraints.

0

4



Figure 11 Same as Figure 10, except for the data corresponding to the second transect.

© 2017 European Association of Geoscientists & Engineers, Near Surface Geophysics, 2017, 15, 210-224

We developed a ground prediction system that uses SH waves for imaging in front of a TBM, in the case of unconsolidated soils. Compared to the conventional systems, this system produces subsurface images with less artefacts, in an automated way. Seismic data are acquired by the receivers on the cutter head of the TBM, which also hosts the vibrators. The design of the vibrator is based on linear synchronous motor technology that is capable of generating low frequencies. With these low 11 frequencies, the seismic system can use FWI as an imaging 12 engine and estimate the shear-wave velocity model required for 13 subsurface imaging in a fully automatic way, without human intervention. In addition to shear-wave velocity, our FWI algorithm estimates the source-related filters and the receiver-coupling factors.

We investigated the potential of the seismic system using both synthetic and field experiments with TBM configurations. The 19 synthetic examples use different acquisition geometries that take 20 practical constraints into account. We showed that the output 21 subsurface image quality goes up by almost a factor of 2 when 22 an acquisition with properly distributed sources and receivers is 23 used. In the case of the field experiments, the system was able to 24 detect a buried object in the subsurface. Hence, our ground pre-25 diction system can be used for hazard assessment during TBM 26 operation in soft soils.

ACKNOWLEDGEMENTS

29 This work is a part of the NeTTUN project, funded by the 30 European Commission's Seventh Framework Programme for Research, Technological Development and Demonstration (FP7 31 32 2007-2013) under Grant Agreement 280712. This work was 33 sponsored by NWO Exacte Wetenschappen (Physical Sciences) 34 for the use of supercomputer facilities, with financial support 35 from the Nederlandse Organisatie voor Wetenschappelijk 36 Onderzoek (Netherlands Organisation for Scientific Research, 37 NWO). Part of the computations was carried out on the Dutch 38 national e-infrastructure with the support of the SURF Foundation 39 (www.surfsara.nl).

REFERENCES

- Ashida Y. 2001. Seismic imaging ahead of a tunnel face with threecomponent geophones. International Journal of Rock Mechanics and Mining Sciences 38(6), 823-831.
- Bellino A., Garibaldi L. and Godio A. 2013. An automatic method for data processing of seismic data in tunneling. Journal of Applied Geophysics 98, 243–253.
- Bharadwaj P., Mulder W.A., Drijkoningen G.G. and Reijnen R. 2015. 47 Looking ahead of a tunnel boring machine with 2-D SH full waveform 48 inversion. 77th EAGE Conference and Exhibition, Madrid, Spain, June 49 2015
- 50 Bharadwaj P., Mulder W. and Drijkoningen G. 2016. Full waveform 51 inversion with an auxiliary bump functional. Geophysical Journal International 206(2), 1076-1092. 52
- Bohlen T., Lorang U., Rabbel W., Müller C., Giese R., Lüth S. et al. 2007. 53 Rayleigh-to-shear wave conversion at the tunnel face: from 3D-FD 54 modeling to ahead-of-drill exploration. Geophysics 72(6), T67-T79. 55

- Boonyasiriwat C., Valasek P., Routh P., Cao W., Schuster G.T. and Macy B. 2009. An efficient multiscale method for time-domain waveform tomography. Geophysics 74(6), WCC59-WCC68.
- Bozdağ E., Trampert J. and Tromp J. 2011. Misfit functions for full waveform inversion based on instantaneous phase and envelope measurements. Geophysical Journal International 185(2), 845-870.
- Bretaudeau F., Brossier R., Leparoux D., Abraham O. and Virieux J. 2013. 2D elastic full-waveform imaging of the near-surface: application to synthetic and physical modelling data sets. Near Surface Geophysics 11(3), 307–316.
- Brossier R., Operto S. and Virieux J. 2009. Seismic imaging of complex onshore structures by 2D elastic frequency-domain full-waveform inversion. Geophysics 74(6), WCC105-WCC118.
- Bunks C., Saleck F.M., Zaleski S. and Chavent G. 1995. Multiscale seismic waveform inversion. Geophysics 60(5), 1457-1473.
- Fichtner A. 2010. Full Seismic Waveform Modelling and Inversion. Springer.
- Ghose R., Nijhof V., Brouwer J., Matsubara Y., Kaida Y. and Takahashi T. 1998. Shallow to very shallow, high-resolution reflection seismic using a portable vibrator system. Geophysics 63(4), 1295-1309.
- Guy E.D., Nolen-Hoeksema R.C., Daniels J.J. and Lefchik T. 2003. High-resolution SH-wave seismic reflection investigations near a coal mine-related roadway collapse feature. Journal of Applied Geophysics 54(1), 51-70.
- Haines S.S. and Ellefsen K.J. 2010. Shear-wave seismic reflection studies of unconsolidated sediments in the near surface. Geophysics 75(2), B59-B66.
- Harmankaya U., Kaslilar A., Wapenaar K. and Draganov D. 2016. Locating scatterers ahead of a tunnel boring machine using noise correlation. 78th EAGE Conference and Exhibition, Vienna, Austria, May-June 2016.
- Hauser E.C. 2001. Detection and location of obstructions ahead of a tunnel boring machine using the tunneling vibrations as a seismic source: the first successful example. 2001 Symposium on Application of Geophysics to Environmental and Engineering Problems (SAGEEP).
- Helbig K. and Mesdag C.S. 1982. The potential of shear-wave observations. Geophysical Prospecting 30(4), 413-431.
- Jetschny S. 2010. Seismic prediction and imaging of geological structures ahead of a tunnel using surface waves. PhD thesis, Karlsruhe Institute of Technology, Germany.
- Kneib G., Kassel A. and Lorenz K. 2000. Automatic seismic prediction ahead of the tunnel boring machine. First Break 18(7).
- Kuvshinov B.N. and Mulder W.A. 2006. The exact solution of the timeharmonic wave equation for a linear velocity profile. Geophysical Journal International 167(2), 659-662.
- Li Y.E. and Demanet L. 2016. Full-waveform inversion with extrapolated low-frequency data. Geophysics 81(6), R339-R348.
- Luo Y., Xia J., Xu Y., Zeng C. and Liu J. 2010. Finite-difference modeling and dispersion analysis of high-frequency Love waves for nearsurface applications. Pure and Applied Geophysics 167(12), 1525-1536.
- Maurer H., Greenhalgh S.A., Manukyan E., Marelli S. and Green A.G. 2012. Receiver-coupling effects in seismic waveform inversions. Geophysics 77(1), R57-R63.
- Miller R.D., Xia J. and Park C.B. 2001. Love waves: a menace to shallow shear wave reflection surveying. 71st SEG annual meeting, Expanded Abstracts, 1377-1380.
- Mulder W.A. and Plessix R.-E. 2008. Exploring some issues in acoustic full waveform inversion. Geophysical Prospecting 56(6), 827-841.
- Musayev K., Hackl K. and Baitsch M. 2013. Frequency domain waveform inversion in a tunnel environment. Proceedings of Applied Mathematics and Mechanics 13(1), 323-324.

4

5

6

7

8

9

1

27

28

40

41

42

43

44

45

4

5

6

7

8

9

11

12

13

14

15

16

17

18

19 20

23

- Nemeth T., Wu C. and Schuster G.T. 1999. Least-squares migration of incomplete reflection data. *Geophysics* 64(1), 208–221.
- Noorlandt R., Drijkoningen G., Dams J. and Jenneskens R. 2015. A seismic vertical vibrator driven by linear synchronous motors. *Geophysics* 80(2), EN57–EN67.
- Omnes G. 1978. Exploring with SH-waves. Canadian Journal of Exploration Geophysics 14, 40–49.
- Petronio L. and Poletto F. 2002. Seismic-while-drilling by using tunnel boring machine noise. *Geophysics* **67**(6), 1798–1809.
- Poletto F. and Petronio L. 2006. Seismic interferometry with a TBM source of transmitted and reflected waves. *Geophysics* 71(4), SI85–SI93.
- Pratt R.G., Shin C. and Hicks G.J. 1998. Gauss–Newton and full Newton methods in frequency–space seismic waveform inversion. *Geophysical Journal International* 133(2), 341–362.
- Steeples D.W. and Miller R.D. 1998. Avoiding pitfalls in shallow seismic reflection surveys. *Geophysics* **63**(4), 1213–1224.
- Stümpel H., Kähler S., Meissner R. and Milkereit B. 1984. The use of seismic shear waves and compressional waves for lithological problems of shallow sediments. *Geophysical Prospecting* 32(4), 662–675.

- Swinnen G., Thorbecke J.W. and Drijkoningen G.G. 2007. Seismic imaging from a TBM. *Rock Mechanics and Rock Engineering* 40(6), 577–590.
- Tarantola A. 1984. Inversion of seismic reflection data in the acoustic approximation. *Geophysics* **49**(8), 1259–1266.
- Tarantola A. 1986. Strategy for nonlinear elastic inversion of seismic reflection data. *Geophysics* **51**, 1893–1903.
- Tzavaras J. 2010. 3D tunnel seismic imaging. PhD thesis, Freie Universität Berlin, Germany.
- van Leeuwen T. and Mulder W.A. 2010. A correlation-based misfit criterion for wave-equation traveltime tomography. *Geophysical Journal International* 182(3), 1383–1394.
- Virieux J. 1984. SH-wave propagation in heterogeneous media: velocitystress finite-difference method. *Geophysics* 49(11), 1933–1942.
- Virieux J. and Operto S. 2009. An overview of full-waveform inversion in exploration geophysics. *Geophysics* 74(6), WCC1–WCC26.
- Wapenaar C.P.A., Verschuur D.J. and Herrmann P. 1992. Amplitude preprocessing of single and multicomponent seismic data. *Geophysics* 57(9), 1178–1188.

iew publication stats